

SA 07.2 – SA 16.2



Electrical data multi-turn actuators for open-close duty with 3-phase AC motors

Short-time duty S2 - 15 min, 400 V/50 Hz

Multi-turn actuator			Motor									
Type	Output speed [rpm]	Max. torque [Nm]	Motor type	Nominal power ¹⁾ P _N [kW]	Speed [rpm]	Nominal current ²⁾ I _N (A)	Max. current ³⁾ I _{max} [A]	Starting current I _A [A]	cos φ	Overcurr. prot. device setting [A]	AUMA power class for switchgear	
											Contactor	Thyristor
SA 07.2	4	30	VD00063-4-0,02	0.02	1,400	0.4	0.4	1.0	0.40	0.4	A1	B1
	5.6					0.4	0.4	1.0	0.40	0.4	A1	B1
	8		VD00063-4-0,04	0.04	1,400	0.4	0.4	1.0	0.50	0.4	A1	B1
	11					0.4	0.5	1.0	0.50	0.5	A1	B1
	16		VD00063-2-0,06	0.06	2,800	0.6	0.6	1.9	0.57	0.6	A1	B1
	22					0.6	0.7	1.9	0.57	0.7	A1	B1
	32		AD00063-4-0,10	0.10	1,400	1.0	1.0	2.4	0.42	1.0	A1	B1
	45					1.0	1.0	2.4	0.42	1.0	A1	B1
	63		AD00063-2-0,20	0.20	2,800	0.8	1.2	4.4	0.60	1.2	A1	B1
	90					0.8	1.3	4.4	0.60	1.3	A1	B1
125	AD00063-2-0,30	0.30	2,800	0.9	1.5	4.4	0.70	1.5	A1	B1		
180				0.9	1.6	4.4	0.70	1.6	A1	B1		
SA 07.6	4	60	VD00063-4-0,03	0.03	1,400	0.4	0.4	1.0	0.43	0.4	A1	B1
	5.6					0.4	0.5	1.0	0.43	0.5	A1	B1
	8		VD00063-4-0,06	0.06	1,400	0.6	0.7	1.6	0.38	0.7	A1	B1
	11					0.6	0.7	1.6	0.38	0.7	A1	B1
	16		VD00063-2-0,12	0.12	2,800	0.7	0.9	3.0	0.52	0.9	A1	B1
	22					0.7	1.0	3.0	0.52	1.0	A1	B1
	32		AD00063-4-0,20	0.20	1,400	1.6	1.9	4.6	0.42	1.9	A1	B1
	45					1.6	2.0	4.6	0.42	2.0	A1	B1
	63		AD00063-2-0,40	0.40	2,800	1.6	2.3	9.0	0.53	2.3	A1	B1
	90					1.6	2.5	9.0	0.53	2.5	A1	B1
125	AD00063-2-0,50	0.50	2,800	1.7	3.0	9.0	0.62	3.0	A1	B1		
180				1.7	3.2	9.0	0.62	3.2	A1	B1		
SA 10.2	4	120	VD00071-4-0,06	0.06	1,400	0.5	0.6	2.0	0.40	0.6	A1	B1
	5.6					0.5	0.6	2.0	0.40	0.6	A1	B1
	8		VD00071-4-0,12	0.12	1,400	1.0	1.1	3.0	0.40	1.1	A1	B1
	11					1.0	1.2	3.0	0.40	1.2	A1	B1
	16		VD00071-2-0,25	0.25	2,800	1.3	1.5	4.5	0.52	1.5	A1	B1
	22					1.3	1.8	4.5	0.52	1.8	A1	B1
	32		AD00071-4-0,40	0.40	1,400	2.5	2.6	8.5	0.42	2.6	A1	B1
	45					2.5	3.0	8.5	0.42	3.0	A1	B1
	63		AD00071-2-0,70	0.70	2,800	3.0	3.6	16	0.54	3.6	A1	B1
	90					3.0	4.0	16	0.54	4.0	A1	B1
125	AD00071-2-1,00	1.00	2,800	3.5	5.2	16	0.64	5.2	A1	B1		
180				3.5	5.5	16	0.64	5.5	A1	B1		
SA 14.2	4	250	VD00090-4-0,12	0.12	1,400	0.5	0.8	2.8	0.60	0.8	A1	B1
	5.6					0.5	1.0	2.8	0.60	1.0	A1	B1
	8		VD00090-4-0,25	0.25	1,400	1.0	1.6	5.2	0.60	1.6	A1	B1
	11					1.0	1.7	5.2	0.60	1.7	A1	B1
	16		VD00090-2-0,45	0.45	2,800	1.5	3.0	9.0	0.64	3.0	A1	B1
	22					1.5	3.5	9.0	0.64	3.5	A1	B1
	32		AD00090-4-0,75	0.75	1,400	2.5	4.0	16	0.62	4.0	A1	B1
	45					2.5	5.0	16	0.62	5.0	A1	B1
	63		AD00090-2-1,40	1.40	2,800	4.7	7.0	38	0.60	7.0	A2	B2
	90					4.7	9.0	38	0.60	9.0	A2	B2
125	AD00090-2-1,80	1.80	2,800	5.3	11	38	0.65	11	A2	B2		
180				5.3	11	38	0.65	11	A2	B2		
SA 14.6	4	500	VD00090-4-0,20	0.20	1,400	0.9	0.9	5.2	0.54	0.9	A1	B1
	5.6					0.9	1.0	5.2	0.54	1.0	A1	B1
	8		VD00090-4-0,40	0.40	1,400	1.7	3.0	9.3	0.56	3.0	A1	B1
	11					1.7	3.5	9.3	0.56	3.5	A1	B1
	16		VD00090-2-0,80	0.80	2,800	3.6	5.0	18	0.51	5.0	A1	B1
	22					3.6	5.5	18	0.51	5.5	A1	B1
	32		AD00090-4-1,60	1.60	1,400	5.3	7.5	38	0.57	7.5	A2	B2
	45					5.3	9.0	38	0.57	9.0	A2	B2
	63		AD00090-2-3,00	3.00	2,800	9.0	13	58	0.60	13	A2	B3
	90					9.0	16	58	0.60	16	A2	B3
125	AD00090-2-3,30	3.30	2,800	9.5	21	58	0.65	18	A2	B3		
180				9.5	22	58	0.65	18	A2	B3		
SA 16.2	4	1,000	VD00112-4-0,40	0.40	1,400	1.4	2.7	10	0.65	2.7	A1	B1
	5.6					1.4	2.9	10	0.65	2.9	A1	B1
	8		VD00112-4-0,80	0.80	1,400	2.8	5.0	22	0.57	5.0	A1	B2
	11					2.8	5.5	22	0.57	5.5	A1	B2
	16		VD00112-2-1,50	1.50	2,800	5.6	9	40	0.60	9	A2	B2
	22					5.6	11	40	0.60	11	A2	B2
	32		AD00112-4-3,00	3.00	1,400	8.5	13	60	0.71	13	A2	B3
	45					8.5	16	60	0.71	16	A2	B3
	63		AD00112-2-5,00	5.00	2,800	11	25	114	0.80	25	A2	–
	90					11	30	114	0.80	25	A2	–
125	AD00112-2-6,00	6.00	2,800	12	35	114	0.83	25	A2	–		
180				12	45	114	0.83	25	A2	–		

1) – 3) Refer to notes on page 2.

We reserve the right to alter data according to improvements made. Previous documents become invalid with the issue of this document.

Electrical data multi-turn actuators for open-close duty with 3-phase AC motors

Short-time duty S2 - 15 min, 400 V/50 Hz

Notes on table	
1) Nominal power P_N	Mechanical power output at motor shaft at running torque of multi-turn actuator (corresponds to approx. 35 % of maximum torque). The consumed electrical power can be calculated using the following formula: $P = U \times I \times \cos \varphi \times \sqrt{3}$
2) Nominal current I_N	Current at running torque
3) Max. current I_{max}	Current at maximum torque

Notes on installation and sizing																																								
Motor data	Motor data is approximate. Due to usual manufacturing tolerances, there may be deviations from the values given.																																							
Thermoswitches/PTC thermistors	To protect against overheating, thermoswitches or PTC thermistors are embedded in the motor windings. Actuators without integral controls (AUMA NORM): Thermoswitches or PTC thermistors have to be considered within the external controls (refer to terminal plan). Note: Failure to connect thermoswitches or PTC thermistors shall void the warranty for the motor. Rating of the thermoswitches <table border="1" style="margin-left: 20px;"> <thead> <tr> <th colspan="2">AC current</th> <th colspan="2">DC current</th> </tr> </thead> <tbody> <tr> <td colspan="2">250 V, 50 – 60 Hz</td> <td>60 V</td> <td>1.0 A</td> </tr> <tr> <td>$\cos \varphi = 1$</td> <td>2.5 A</td> <td>42 V</td> <td>1.2 A</td> </tr> <tr> <td>$\cos \varphi = 0.6$</td> <td>1.6 A</td> <td>24 V</td> <td>1.5 A</td> </tr> </tbody> </table> Actuators with AM or AC integral controls: Thermal motor protection is already integrated.	AC current		DC current		250 V, 50 – 60 Hz		60 V	1.0 A	$\cos \varphi = 1$	2.5 A	42 V	1.2 A	$\cos \varphi = 0.6$	1.6 A	24 V	1.5 A																							
AC current		DC current																																						
250 V, 50 – 60 Hz		60 V	1.0 A																																					
$\cos \varphi = 1$	2.5 A	42 V	1.2 A																																					
$\cos \varphi = 0.6$	1.6 A	24 V	1.5 A																																					
Mains voltage, mains frequency	Permissible variation of mains voltage: $\pm 10\%$ Permissible variation of mains frequency: $\pm 5\%$																																							
Switchgear sizing	For motor operation, reversing contactors (mechanically, electrically and electronically locked) or thyristors (electronically locked) can be used. Actuators without integral controls (AUMA NORM): Switchgear are supplied by the customer. We recommend specification of switchgear suitable for their rated operating power/motor power in compliance with the assigned AUMA power class. Switchgear assignment to AUMA power classes: <table border="1" style="margin-left: 20px;"> <thead> <tr> <th rowspan="2">AUMA power class</th> <th rowspan="2">Reversing contactor Rated operating power acc. to EN 60947-4-1 Utilization category AC-3</th> <th colspan="2">Reversing contactor Motor power according to UL/CSA at</th> </tr> <tr> <th>480 V AC</th> <th>600 V AC</th> </tr> </thead> <tbody> <tr> <td>A1</td> <td>4.0 kW</td> <td>5.0 hp</td> <td>5.0 hp</td> </tr> <tr> <td>A2</td> <td>7.5 kW</td> <td>10 hp</td> <td>10 hp</td> </tr> <tr> <td>A3</td> <td>15 kW</td> <td>20 hp</td> <td>25 hp</td> </tr> <tr> <td>A4</td> <td>30 kW</td> <td>60 hp</td> <td>60 hp</td> </tr> <tr> <td>A5</td> <td>55 kW</td> <td>75 hp</td> <td>100 hp</td> </tr> <tr> <td>A6</td> <td>75 kW</td> <td>100 hp</td> <td>125 hp</td> </tr> </tbody> </table> <table border="1" style="margin-left: 20px;"> <thead> <tr> <th rowspan="2">AUMA power class</th> <th rowspan="2">Thyristor Rated operating current acc. to EN 60947-4-2 Utilization category AC-53a</th> </tr> <tr> <th>400 V AC</th> </tr> </thead> <tbody> <tr> <td>B1</td> <td>6 A</td> </tr> <tr> <td>B2</td> <td>8.5 A</td> </tr> <tr> <td>B3</td> <td>16 A</td> </tr> </tbody> </table> Actuators with AM or AC integral controls: Required switchgear in power classes A1 – A3 or B1 – B3 are already integrated in AM or AC controls. For switchgear of power classes A4 – A6, a control box is additionally required. For actuators with AM integral actuator controls and installed switchgear in AUMA power class A3, an optional thermal overcurrent protection device cannot be directly integrated within the AM. An additional control box is required. However, AC actuator controls can be used instead of AM controls. When opting for AC controls, the additional control box can be omitted.	AUMA power class	Reversing contactor Rated operating power acc. to EN 60947-4-1 Utilization category AC-3	Reversing contactor Motor power according to UL/CSA at		480 V AC	600 V AC	A1	4.0 kW	5.0 hp	5.0 hp	A2	7.5 kW	10 hp	10 hp	A3	15 kW	20 hp	25 hp	A4	30 kW	60 hp	60 hp	A5	55 kW	75 hp	100 hp	A6	75 kW	100 hp	125 hp	AUMA power class	Thyristor Rated operating current acc. to EN 60947-4-2 Utilization category AC-53a	400 V AC	B1	6 A	B2	8.5 A	B3	16 A
AUMA power class	Reversing contactor Rated operating power acc. to EN 60947-4-1 Utilization category AC-3			Reversing contactor Motor power according to UL/CSA at																																				
		480 V AC	600 V AC																																					
A1	4.0 kW	5.0 hp	5.0 hp																																					
A2	7.5 kW	10 hp	10 hp																																					
A3	15 kW	20 hp	25 hp																																					
A4	30 kW	60 hp	60 hp																																					
A5	55 kW	75 hp	100 hp																																					
A6	75 kW	100 hp	125 hp																																					
AUMA power class	Thyristor Rated operating current acc. to EN 60947-4-2 Utilization category AC-53a																																							
		400 V AC																																						
B1	6 A																																							
B2	8.5 A																																							
B3	16 A																																							