

| Multi-turn actuator | | | | Motor | | | | |
|---------------------|-------------------------|---------------------------|---------------------------|--------------------|---------------------------|-------------|--|---|
| Type | Output speed Max. [rpm] | Torque range | | Motor type | Power ¹⁾ P [W] | Speed [rpm] | Nominal current ²⁾ I _N [A] | Starting current ³⁾ I _{max} [A] |
| | | Open-close duty max. [Nm] | Modulating duty max. [Nm] | | | | | |
| SD 05 | 8 | 6 | 6 | sm ⁵⁾ | 50 | 450 | 0.22 | 0.22 |
| SD 10 | 20 | 10 | 10 | bldc ⁶⁾ | 60 | 4 500 | 0.26 | 0.26 |
| SD 25 | 20 | 30 | 25 | bldc ⁶⁾ | 120 | 4 500 | 0.52 | 0.52 |

Notes on table

| | | |
|----|-----------------------------------|-------------------------------------|
| 1 | Power P | Maximum power consumption |
| 2) | Nominal current I _N | Current at running torque |
| 3) | Starting current I _{max} | Maximum short-term starting current |
| 4) | | Step motor |
| 5) | | Brushless DC motor |